Data sheet

6ES7522-1BH10-0AA0



SIMATIC S7-1500, digital output module, DQ16xDC 24V/0.5A BA, 16 channels in groups of 8, 4 A per group; the module supports the safety-oriented shutdown of load groups up to SIL2 according to EN IEC 62061:2021 and Category 3 / PL d according to EN ISO 13849-1:2015. delivery incl. front connector push-in

General information		
Product type designation	DQ 16x24VDC/0.5A BA	
HW functional status	From FS01	
Firmware version	V1.0.0	
 FW update possible 	Yes	
Product function		
 I&M data 	Yes; I&M0 to I&M3	
 Isochronous mode 	No	
Prioritized startup	Yes	
Engineering with		
 STEP 7 TIA Portal configurable/integrated from version 	V13 / V13	
 STEP 7 configurable/integrated from version 	V5.5 SP3 / -	
 PROFIBUS from GSD version/GSD revision 	V1.0 / V5.1	
 PROFINET from GSD version/GSD revision 	V2.3 / -	
Operating mode		
• DQ	Yes	
 DQ with energy-saving function 	No	
• PWM	No	
 Oversampling 	No	
• MSO	Yes	
Supply voltage		
Rated value (DC)	24 V	
permissible range, lower limit (DC)	19.2 V	
permissible range, upper limit (DC)	28.8 V	
Reverse polarity protection	Yes; through internal protection with 7 A per group	
Input current		
Current consumption, max.	30 mA	
output voltage / header		
Rated value (DC)	24 V	
Power		
Power available from the backplane bus	1.15 W	
Power loss		
Power loss, typ.	2.2 W	
Digital outputs		
Type of digital output	Transistor	
Number of digital outputs	16	
Current-sourcing	Yes	
Digital outputs, parameterizable	No	
Short-circuit protection	Yes	

Response threshold, typ.	1 A
Limitation of inductive shutdown voltage to	L+ (-53 V)
Controlling a digital input	Yes
Switching capacity of the outputs	
 with resistive load, max. 	0.5 A
on lamp load, max.	5 W
Load resistance range	
lower limit	48 Ω
• upper limit	12 kΩ
Output voltage	
• for signal "1", min.	L+ (-0.8 V)
Output current	
for signal "1" rated value	0.5 A
 for signal "1" permissible range, max. 	0.5 A
for signal "0" residual current, max.	0.5 mA
Output delay with resistive load	
• "0" to "1", max.	100 μs
• "1" to "0", max.	500 µs
Parallel switching of two outputs	300 μ3
• for logic links	Yes
_	
• for uprating	No Yes
for redundant control of a load Cuitabing fragueagy	Yes
Switching frequency	400 11-
with resistive load, max.	100 Hz
with inductive load, max.	0.5 Hz; According to IEC 60947-5-1, DC-13
on lamp load, max.	10 Hz
Total current of the outputs	
 Current per channel, max. 	0.5 A; see additional description in the manual
 Current per group, max. 	4 A; see additional description in the manual
Current per module, max.	8 A; see additional description in the manual
Cable length	
shielded, max.	1 000 m
• unshielded, max.	600 m
unshielded, max. Interrupts/diagnostics/status information	600 m
Interrupts/diagnostics/status information	
Interrupts/diagnostics/status information Diagnostics function	No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable	
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms	No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm	No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt	No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses	No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage	No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break	No No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit	No No No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error	No No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED	No No No No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED	No N
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED	No Yes; green LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED)	No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED) • Channel status display	No Yes; green LED Yes; red LED
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED)	No Yes; green LED Yes; red LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED) • Channel status display	No Yes; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms • Diagnostic alarm • Maintenance interrupt Diagnoses • Monitoring the supply voltage • Wire-break • Short-circuit • Group error Diagnostics indication LED • RUN LED • ERROR LED • Monitoring of the supply voltage (PWR-LED) • Channel status display • for channel diagnostics • for module diagnostics	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation	No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics Potential separation Potential separation channels between the channels	No Yes; green LED Yes; red LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RUN LED REROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of	No Yes; green LED Yes; green LED Yes; green LED Yos; green LED No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus	No Yes; green LED Yes; red LED Yes; green LED Yes; green LED No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus	No No No No No No No No No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics Potential separation Potential separation channels between the channels, in groups of between the channels and backplane bus	No Yes; green LED Yes; green LED Yes; green LED Yos; green LED No No No No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED ERROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus	No No No No No No No No No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Isolation Isolation tested with Standards, approvals, certificates	No No No No No No No No No Ves; green LED Yes; red LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions	No No No No No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions Suitable for safety-related tripping of standard modules	No No No No No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No
Interrupts/diagnostics/status information Diagnostics function Substitute values connectable Alarms Diagnostic alarm Maintenance interrupt Diagnoses Monitoring the supply voltage Wire-break Short-circuit Group error Diagnostics indication LED RUN LED RROR LED Monitoring of the supply voltage (PWR-LED) Channel status display for channel diagnostics for module diagnostics for module diagnostics between the channels between the channels between the channels and backplane bus Isolation Isolation Isolation tested with Standards, approvals, certificates Suitable for safety functions	No No No No No No No No No Ves; green LED Yes; green LED Yes; green LED Yes; green LED No

 Category according to ISO 13849-1 SIL acc. to IEC 62061 remark on safety-oriented shutdown 	Cat. 3 SIL 2 https://support.industry.siemens.com/cs/de/de/view/39198632
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-30 °C; from FS04
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C; from FS04
 vertical installation, max. 	40 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	25 mm
Height	147 mm
Depth	129 mm
Weights	
Weight, approx.	230 g
Other	
Note:	Supplied incl. 40-pole push-in front connectors
last modified:	5/6/2022 🗗