



Figure similar

MLFB-Ordering data

6SL3210-5BB11-2UV1

Client order no. :

Order no. :

Offer no. :

Remarks :

Item no. :

Consignment no. :

Project :

| Rated data | | General tech. specifications | |
|-------------------------|---------------------------|--|---|
| Input | | Power factor λ | 0.72 |
| Number of phases | 1 AC | Offset factor $\cos \varphi$ | 0.95 |
| Line voltage | 200 ... 240 V -15 % +10 % | Efficiency η | 0.98 |
| Line frequency | 47 ... 63 Hz | Ambient conditions | |
| Output | | Cooling | convection cooling |
| Number of phases | 3 AC | Installation altitude | 1000 m (3281 ft) |
| Rated voltage | 230 V | Ambient temperature | |
| Rated power (HO) | 0.12 kW / 0.16 hp | Operation | -10 ... 60 °C (14 ... 140 °F) |
| Rated power (LO) | 0.12 kW / 0.12 hp | Storage | -40 ... 70 °C (-40 ... 158 °F) |
| Rated current (HO) | 0.90 A | Relative humidity | |
| Rated current (LO) | 0.90 A | Max. operation | 95 % |
| Pulse frequency | | Communication | |
| Pulse frequency | 8.00 kHz | Communication | USS, Modbus RTU |
| Output frequency | 0 ... 550 Hz | Standards | |
| | | Compliance with standards | CE, cULus, C-Tick (RCM), KC |
| | | CE marking | EN 61800-5-1 /EN 60204-1 and EN 61800-3 |

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



Figure similar

MLFB-Ordering data

6SL3210-5BB11-2UV1

Mechanical data

| | |
|----------------------|---------------------------------------|
| Mounting position | Wall mounting / side-by-side mounting |
| Degree of protection | IP20 |
| Size | FSAA |
| Net weight | 0.70 kg (1.54 lb) |
| Width | 68.0 mm (2.68 in) |
| Height | 142.0 mm (5.59 in) |
| Depth | 107.8 mm (4.24 in) |

Connections

Max. motor cable length

| | |
|------------|---------------|
| Shielded | 25 m (33 ft) |
| Unshielded | 50 m (164 ft) |

Inputs / outputs

Standard digital inputs

| | |
|--------|---|
| Number | 4 |
|--------|---|

Digital outputs

| | |
|------------------------------------|---|
| Number as relay changeover contact | 1 |
|------------------------------------|---|

| | |
|----------------------|---|
| Number as transistor | 1 |
|----------------------|---|

Analog inputs

| | |
|--------|---|
| Number | 2 (Can be used as additional digital input) |
|--------|---|

Analog outputs

| | |
|--------|---|
| Number | 1 |
|--------|---|